



BOAB



12Volt – 55Amp DC - HIGH POWER REMOTE AREA – CAMPING / VEHICLE BATTERY CHARGER

www.BOAB.biz

ORIGINALLY AN AUSTRALIAN IDEA, THIS REMOTE AREA BATTERY CHARGER WAS DESIGNED TO MEET THE NEEDS OF NOT JUST OUTBACK TRAVELLERS, BUT ALSO FARMING, MINING, QUARRYING, PLANT AND CONSTRUCTION COMPANIES. PROVIDING REMOTE AREA USERS WITH A QUICK AND RELIABLE REMEDY TO FLAT BATTERIES.

AUSTRALIAN COMPONENTS, ASSEMBLED IN ENGLAND, USING HONDA POWER

SPECIFICATIONS:

| | |
|----------------------|----------------------------------|
| Weight: | 12kg |
| Dimensions (mm) | 410 x 275 x 370 (L x W x H) |
| Alternator: | Australian designed Bosch 55 amp |
| Electrical output: | 12 volts DC. |
| Max voltage (low): | 14.2 volts regulated |
| Max voltage (high): | 15.0 volts regulated |
| Max amp output: | 55 amps |
| Voltage cut out: | 18 volts |
| Charge Display: | Red Digital LED Readout (00.0)* |
| Charge Indicator: | Switched Amps or Volts |
| Honda Engine: | 50cc air-cooled 4stroke OHV |
| Max eng. power: | 2.5hp (1.8kw) @ 7000rpm |
| Fuel capacity: | 1.2 litres (unleaded) |
| Fuel consumption: | Approx. ¾ litre/hour |
| Oil capacity: | 0.25 litres |
| Starting system: | Recoil |
| Noise Level: | Max 74dba @ 7metres |



FEATURES INCLUDE:

- Environmentally friendly UK/EU compliant Honda GXH50 engine, with worldwide guarantee.
- Australian made electrics & Bosch alternator with worldwide guarantee.
- Low oil level warning buzzer
- Low or High charge rate, at the flick of a switch
- Short circuit and over voltage protection.
- DC power immediately when required
- Digital LED readout to one decimal place (00.0amps)
- Digital LED readout Volts (momentary switch)
- Lightweight, only 26lbs (12kg)
- High current Leads, 3m long with insulated alligator clamps.
- Over 90mins charging per fuel tank filling
- Designed to charge a single battery.
- Assembled in England by **BOAB**



USES:

- Marine & boating - emergency services – heavy plant & machinery, construction & earthmoving contractors
- mobile mechanics - caravans & mobile homes - trucking, recovery & breakdown services or anyone working or travelling in the outback or remote areas, where flat batteries could be a life threatening dilemma.
- Users can supply enough charge in as little as 5 minutes to start heavy machinery.
- Campers can run fridges for 24 hours then charge their batteries in under 1 hour.
- 12 Volt lighting or other appliances can be powered in emergency situations.
- Example of Charge Rate; Land Rover 300Tdi with flat battery takes approx 3-5 minutes to charge suitable for starting.

PRICE:

“Deluxe Model” 55 amp, 2.5hp Battery Charger c/w Digital LED Volt & Amp Charge Readouts: £1169:00 (inc 20% VAT)